URGENT!! MUST READ!!

If you are not the race secretary, please inform your race secretary of these new changes

The Unikon bands are a brand new chip ring band. This new band uses the most up to date, and highest security RFD chip available.

This will require an upgrade to the software on the club data logger and the club antenna, before basketing for a race. Easy on screen instructions will guide you along. After you install these programs, the old style bands will continue to work.

You will want to download the following two programs:

Club Antenna Upgrade

click here to download <u>anc250us.exe</u> (this updates the club antenna)

(Make sure you have a memory module in the datalogger)

1. Connect the data logger with the COM port of the PC, using the original PC cable.

2. Click the "Update" button to start the update.

3. Swith the Unikon datalogger on and hold the key "0" until the message "ESA PROG Mode" appears on the LCD screen

4. IMMEDIATELY connect the Unikon club antenna to the Unikon data logger. (you only have a couple of seconds to do this connection, so be ready. The on screen instructions do not convey how quickly you must plug the club antenna in.

Below is a screen shot of what you will see:

UnikonUpdate
Communications Fort (COM1) Update
UNIKON ANC UPDATE includes: ANC Firmware: v2.50 US 03.12.2007
In order to perform the update, please follow these steps: 1.) Connect the UNIKON PCF with the COM port of the PC, using
the original PC cable. 2.) Click the 'Update' button to start the update. 3.) Switch the UNIKON PCF on and hold the key '0' until the
4.) Now connect the UNIKON ANC to the UNIKON PCF.

Club Data Logger Upgrade

ucus334_legacy.exe (this updates the club data logger)

(Make sure you have a memory module in the datalogger)

- 1. Switch off the Unikon data logger.
- 2. Connect your serial cable (<u>CPC cable</u>) to the side of the data logger,
- 3. Press Update button
- 4. When instructed below with the flashing status bar

switch on your Unikon data logger.

Below is a screen shot of what you will see:

UnikonUpdate
Communications Port (COM1) Update
UNIKON PROFESSIONAL UPDATE includes: PCF App: v3.34 (base station firmware) RBM App: v3.34 (pocket module firmware)
To perform the update, please follow these steps: - Switch off the UNIKON Professional Loft Clock (PCF) - Connect your serial cable to the side of the Loft Clock (PCF)
- Press Update - When instructed below with the flashing status bar switch on your UNIKON Professional Loft Clock (PCF)

<u>Unikon Manual</u> (requires Microsoft Word) <u>Unikon Manual</u> (requires Adobe Acrobat Reader) <u>Adobe Acrobat Reader</u> (free download)

WinSpeed users - read this